## PRODUCT DEFINITION

The VYKON JEC-834 is part of the VYKON portfolio of Java-based controller/server products, software applications and tools designed to integrate a variety of devices and protocols into unified, distributed systems. VYKON products are powered by the Niagara Framework®, the industry's leading software technology that integrates diverse systems and devices into a seamless workflow. The Niagara Framework includes integrated management tools to support the design, configuration and maintenance of a unified, real-time controls network. The JEC-834's Input/Output modules are designed with low voltage power supply, making this package ideal for equipment control.

## **APPLICATIONS**

The JEC-834 is ideal for controlling and monitoring a building system including HVAC equipment, lighting and meters. The included Input/
Output module provides 34 discrete I/O points for local control which can be expanded to more than 250 points of discrete I/O using additional IO R modules. In addition, the JEC-834 supports further expansion when licensed to also control other remote devices. The JEC-834 serves data and rich graphical displays to a standard web browser via an Ethernet LAN or remotely over the Internet. In larger facilities, multi-building applications and large-scale control system integrations, Niagara Supervisor™ software can be used to aggregate information (real-time data, history, alarms, etc.) from large numbers of JACEs into a single unified application.

The VYKON JACE
Equipment Controller
(JEC-834) is an
embedded controller/
server platform
designed for
monitoring and control
applications. The JEC834 is bundled with a
34 point IO R module
and with the same
open drivers as the
JACE 8000 family
of controller/server
products.

## key features

- 34 hardware control points (expandable with other IO R modules).
- Further expansion using standard JACE 8000 drivers
- Web User interface serves rich HTML5 presentations and live data to any browser
- Supports JACE 8000 Communications Modules
- 24 volt AC/DC power supply input
- Din Rail mountable for quick installation



## ORDERING INFORMATION

Part number	Description
JEC-834	JACE®-8000 with 34 point I/O module. JACE 8000 Controller, microSD card, 2 10/100 Mb Ethernet ports, 2 RS-485 serial ports. Licensed for 0 Devices/O Proxy Points. Includes standard open drivers. Requires 24 VAC or 24 VDC Power Source. Option cards required for communication to remote devices are not included. An 18-month software maintenance agreement (SMA) is required for the initial order. 3 or 5 year agreement may be substituted.
	OPTIONS
DEVICE-1	Add 1 device/50 points to initial order
DEVICE-10	Add 10 devices/500 points to initial order
DEVICE-25	Add 25 devices/1,250 points to initial order
DEVICE-50	Add 50 devices/2,500 points to initial order
DEVICE-UP-1	Upgrade of 1 device/50 points to existing license
DEVICE-UP-10	Upgrade of 10 devices/500 points to existing license
DEVICE-UP-25	Upgrade of 25 devices/1,250 points to existing license
DEVICE-UP-50	Upgrade of 50 devices/2,500 points upgrade to existing license
IO-R-16 (16)	8 Universal inputs: Type 3 (10k) thermistors, 0-100K ohm, 0-10VDC, 0-20 mA with external resistor; 4 Relay outputs (Form A contacts, 24VAC @ .5 amp rated); 4 Analog outputs (0-10VDC); Powered from IO-R-34; Connected to JACE 8000 remotely over a shielded RS485 bus
IO-R-34 (8)	16 Universal inputs: Type 3 (10k) thermistors, 0-100K ohm, 0-10VDC, 0-20 mA with external resistor; 10 Relay outputs (Form A contacts, 24VAC @ .5 amp rated); 8 Analog outputs (0-10VDC); Powered from a 24VAC/DC source; Can power up to 4 IO-R-16 modules; Connected to JACE 8000 remotely over a shielded RS485 bus
NPB-8000- 2X-485	JACE 8000 controller—add on dual port RS-485 module
NPB-8000-LON	JACE 8000 controller—add on dual port RS-485 module
NPB-8000-232	JACE 8000 controller—add on single port RS-232 module
WPM-8000	JACE 8000 100-240V universal power supply

Find additional data sheets for the VYKON products on VYKON's website

The JACE 8000 controller is available through a wide variety of Niagara Community partners. Our open distribution business model and open protocol support allow a vendor-neutral application compatible with devices and systems throughout the world.

Contact your VYKON partner today to get started.



vykon.com

 $\odot$  2018 Tridium Inc. All rights reserved. All other trademarks and registered trademarks are properties of their respective owners.

Information and/or specifications published here are current as of the date of publication of this document. Tridium, Inc. reserves the right to change or modify specifications without prior notice. The latest product specifications can be found by contacting our corporate headquarters, Richmond, Virginia. Products or features contained herein may be covered by one or more U.S. or foreign patents. This document may be copied only as expressly authorized by Tridium in writing. It may not otherwise, in whole or in part, be copied, photocopied, reproduced, translated, or reduced to any electronic medium or machine-readable form.